

INSTALLATION AND USER MANUAL FOR THE AB-2 MODULE

Introduction:

This module has been designed to maintain a constant bias voltage through all power output tubes for your tube stereo power amp.

The bias is kept at a constant level on the output tubes, irrespective of the signal level.

Benefits:

The advantage of using the AB-2 module is that it will extend output tube life, in a lot of cases it will also improve the sound and last but not least, you will never have to worry about adjusting the bias again.

- Soft start indication via two red LED's, also acting as fault indication, one for each tube
- Bias reached and steady indication via two blue LED's
- Fault indication via TTL compatible open collector output – terminal 3 (the output may also be used for other protection outputs)
- No need to keep an eye on and/or adjust the bias of the output tubes
- Significant extension of the output tubes life
- Bias is not influenced by the input signal
- Suitable for Single Ended Amps
- Undistorted and improved sound for a great listening experience
- Reduction in hum and noise level of the amp
- No maintenance or additional adjustments are required after the initial setup
- Improved overall operation of the amp due to the reduction in the danger of a tube red plating
- The AB-2 ensures that bias is kept at the pre-set value (see Initial Setup) even as the tubes age
- The AB-2 comes with a soft start feature, which slowly brings up bias to each output tube

Quick Overview:

The AB-2 module has two **blue** LED's, one for each output tube, which when lit, indicate that bias is at the correct level and that all is good with each tube.

The AB-2 module has two **red** LED's, one for each output tube, which at start up indicate 'soft start' for about 20s and then go off, but also double up to show any tube error or bias issue.

After a further delay of between 40-50 sec, each of the **blue** LED's should come on indicating that the bias is now set and stable for each output tube. The amp is now ready to use.

The AB-2 is suitable for all amplifier types (classes A, AB, or B), as well as single ended amplifiers with class A tubes connected in parallel.

Setting the reference current through the tubes using the "**Rref resistor**" on the AB-2 pcb:


The AB-2 module is equipped with a trimmer used for setting the desired current through the tubes. This trimmer can be replaced by the customer. Prepare a standard "reference" resistor (the small leaded resistor **Rref** in the front part of the module as shown in the diagram below) with 3k3 resistor. This resistor produces a constant current of 38mA with 10Ω between the cathode and the ground. Below is a table of values for the **Rref** resistor for the given current and reference voltage value.

Refer to the table below. **Rref1** is the calculated value and **Rref2/Rref** is the closest standard value to be used. In place of the **Rref** resistor, the supplied multiturn trimmer may be installed. If the resistance value is too high, it can be wired in parallel with the **Rref** resistor to limit the amount of adjustable current.

Iref	Vref	Rref1	Rref2	Iref	Vref	Rref1	Rref2	Iref	Vref	Rref1	Rref2
mA	V	Ω	Ω	mA	V	Ω	Ω	mA	V	Ω	Ω
10	0.1	750	750	95	0.95	11K0	11K	180	1.8	44K2	43K
15	0.15	1K1	1K1	100	1	11K5	12K	185	1.85	51K1	51K
20	0.2	1K54	1K5	105	1.05	12K7	13K	190	1.9	56K2	56K
25	0.25	1K96	2K	110	1.1	14K0	14K	195	1.95	61K9	62K
30	0.3	2K37	2K4	115	1.15	15K0	15K	200	2.0	71K5	68K
35	0.35	2K87	2K7	120	1.2	16K2	16K	205	2.05	78K7	75K
40	0.4	3K32	3K3	125	1.25	17K8	18K	210	2.1	90K9	91K
45	0.45	3K83	3K9	130	1.3	18K7	19K	215	2.15	110	110K
50	0.5	4k42	4K3	135	1.35	20K5	20K	220	2.2	127K	130K
55	0.55	4K87	4K7	140	1.4	22K6	22K	225	2.25	162K	160K
60	0.6	5K62	5K6	145	1.45	23K7	24K	230	2.3	205K	200K
65	0.65	6K19	6K2	150	1.5	26K1	25K	235	2.35	274K	270K
70	0.7	6K8	6K8	155	1.55	28K7	27K	240	2.4	422K	430K
75	0.75	7K5	7K5	160	1.6	30K1	30K	245	2.45	866K	820K
80	0.8	8K25	8K2	165	1.54	34K8	33K	250	2.5	open	open
85	0.85	9K09	9K1	170	1.7	36K5	36K				
90	0.9	10K	10K	175	1.75	40k2	39K				

Example: Maximum required current: 60 mA. Theoretical reference – resistor **Rref**, 5K62. If using the 20k trimmer, place the 5K6 resistor in parallel with the trimmer to achieve a combined resistance of 5K815 (the maximum current value is thus only 60 mA).

The circuits of the first grids of the output tubes must be equipped with isolation resistors (marked red with the value 100k) and the cathodes with 10 Ω resistors.




Circuit operation:

- The reference voltage is developed across an exchangeable resistor, **Rref**, or an multiturn trimmer. An external potentiometer may also be used.
- The control loop adjusts the bias so that the current through the sampling resistor (10Ω) produces the same voltage as the reference voltage. This happens very slowly by rejecting the dynamic variations caused by the music.
- During startup, the Active Bias System sets the limit of distortion during this stage to just 15s. During this time the red "Start Up" LED's are on (they may flash briefly as the control loops stabilizes).
- The Active Bias System the slowly starts ramping up the bias voltage, reaching full bias within approx. 45s.
- If a tube is faulty or fails and the desired bias level cannot be reached but it continues to receive increasing current, the relevant red "Start Up" LED will re-light and the "ERROR" output will be pulled low (open collector – terminal pin 3) to allow the external protection circuit/s, if used, to protect the amplifier from the faulty tube.


Installing and wiring the AB-2 module into your tube amp:

Please refer to the drawing below, which shows a typical tube amps connection for your AB-2 module.



Use this diagram as a reference to the wiring of the AB-2 module into your amp.

Below is a wiring diagram showing how the AB-2 module is wired for a Single Ended amp, one channel
Shown



- Connect your amps -ve bias supply to **Terminal 1** on the AB-2, shown as a blue wire in the above drawing
- Connect a wire from your amps star ground to **Terminal 2** on the AB-2, shown as a green wire in the above drawing
- Connect two wires, 6.3V to 12VAC to **Terminals 4 & 5** on the AB-2 module, shown as orange wires in the above drawing

IMPORTANT NOTE about the 6.3V to 12VAC supply:

All auto bias modules without built in transformers WILL NOT WORK if the filament supply in your amp is in any way referenced to ground, such as a center tap! This important point is clearly explained on our web site!

If your amps filament supply is indeed referenced to ground, you MUST use a separate small power transformer for this AB-2 module, around 2VA, with a suitable secondary supply, anything from 6VAC to 12VAC, or use the **ABF-Q module instead which has its own on-board power transformer!**

- Connect a wire from terminal **CATHODE 1** on the AB-2 module to the CATHODE of V1/Tube 1, shown as a brown wire in the above drawing. With almost most power tubes, this is pin 8. We also recommend that you connect the cathode of your tube, if it is a pentode, to the Suppressor grid, with most power tubes this is pin 1
- Connect a wire from terminal **CATHODE 2** on the AB-2 module to the CATHODE of V2/Tube 2, shown as a brown wire in the above drawing. With almost most power tubes, this is pin 8. We also recommend that you connect the cathode of your tube, if it is a pentode, to the Suppressor grid, with most power tubes this is pin 1
- You MUST connect an isolation resistor, 100K, between the **BIAS1** terminal on the AB-2 module and the OUTPUT end of the output coupling capacitor for V1 of your amps circuit, shown as a purple wire in the above diagram
- You MUST connect an isolation resistor, 100K, between the **BIAS2** terminal on the AB-2 module and the OUTPUT end of the output coupling capacitor for V2 of your amps circuit, shown as a purple wire in the above diagram

This now pretty much completes the wiring of the AB-2 module into your tube amp.

Double check all the wiring steps again, even triple check them ☺

Once you are confident that all your wiring is correct and as per the above steps, it is time to test your AB-2 module installation.

Plug in all tubes, that is the driver tubes, power tubes and the tube rectifier. In order to see the blue LED's on the AB-2 module, place your amp on its side.

Maybe stick a piece of Styrofoam under one of the output transformers to cradle the amp chassis so that the tubes do not touch the bench top.

Connect an 8 or 4 OHM dummy load or your speaker.

Power up your amp. The red LED's on the AB-2 module should come on straight away and will go out after about 20s.

After an additional 40 to 50s, each of the blue LED's on the AB-2 module should start to come on, which indicates that each output tube has reached the preset bias level and all is good. Excellent!

You can measure the actual bias voltage on each output tube with a meter just to double check.

Set your volt meter to the 1V, 2V or 5V scale in DC volts. Put the red meter lead on the cathode pin of the tube socket and place the black meter to the chassis star ground tag. The meter should read close to your preset bias voltage. This reading might be a little higher to start with and will get close to or exactly to the preset bias voltage as the output tubes warm up.

Do this measurement for each output tube.

Leave the amp running for about 10 minutes, all four of the blue LED's should remain lit.

Power down the amp and let everything cool down a bit. Remove dummy load, if that's what you used, or disconnect your speaker.

Re assemble your amp and place it in its spot.
Power up your amp and after about 60s or so, the amp is ready!

If things do not work as they are supposed to:

If the **red** LED on the AB-2 module does not come on immediately after the amp is powered up, power it back down and check the wiring/connections two 6,3 AC pads on the AB-2 module. Make sure all is good there!

If none of the **blue** LED's come on after the 40-50s soft start delay, power the amp back down. Check all your wiring from the AB-2 module to your amp.

If say only one of the **blue** LED's come on after the soft start delay, power the amp back down and check the wiring to that particular tube for which the **blue** LED did not go on for. Also check to make sure that the pins in that tube socket are nice and tight and that the tube fits into the socket not at all loose. Also check the pins in the tube socket of any oxidization, if they are dirty, perhaps use Deoxit or similar to clean the pins!

Do's and don'ts:

Do check that the pins in each tube socket are tight and that each tube does not fit loosely in the socket.
Do check that the pins in each tube socket are clean of oxidization, use Deoxit or similar if they are not clean.

Good fitting and clean pins in tube sockets make ALL the difference!!

Don't do a lot of tube rolling! This is a sure way to loosen up the pins in your sockets! If you cannot help yourself and you must do tube rolling, check the tightness of the pins each time you swap tubes!